



SAVANT

QO Dual 20 AMP Relay

GPM-QP2R20120-21

SKU: 179153 UPC: 43168546805

The inCharge Dual 20A Relay Companion Module (120V AC with Current Transformer - QO™ compatible with plug-on neutral) controls up to two 20 amp circuits; ideal for outlets, kitchen appliances, lighting, and more.

Features

- Works with 3/4 inch Schneider/Electric Square D™ QO™ plug-on neutral load centers.
- Supported for use with InCharge Power Systems or as part of a larger Savant Pro system.
- Compatible with Savant Power Director and/or Savant Panel Bridge Controller (PBC-1000), Savant Energy Monitor (SEM)
- Deployment and configuration via Savant Power and Light 2.0 App or through RacePoint Blueprint
- Control Capability for loads up to 2400 VA (volt-ampere) per channel
- Built-in energy monitoring: +/- .5% revenue grade accuracy / 1 sec sample time
- Dynamic remote management of loads
- Communicates via Bluetooth Low Energy (BLE) technology
- Color LCD display for easy identification and load status
- Two switches positioned on front of module allow power to outputs A and B to be toggled manually

Temperature	32° to 104° F (0° to 40° C)
Location	Indoor Use Only
Dimensions	4.97" x 1.45" x 2.60"
Input Power (powers the module)	120V AC (+/- 10%) @ 60 Hz, 0.1A max
Input Power (from feeder breaker)	2120V AC @ max load power
Load Power	2400VA max per channel (20A resistive load / 1 HP max per channel)
Wireless	<ul style="list-style-type: none"> • Bluetooth 5 Low Energy (BLE) • 2.4 GHz radio frequency