



RadioRA 2 RF Maestro LED+ RF Dimmer - Brown

RRD-PRO-BR

SKU: 157487 UPC: 784276270267

Maestro PRO LED+TM dimmer for RadioRA 2 and RA2 Select

RadioRA 2 Maestro local controls function much like standard dimmers and switches, but can be controlled as part of a lighting control system.

RadioRA 2 Maestro dimmers incorporate advanced features such as fade-on/fade-off, delayed long fade-to-off, and rapid full-on. RadioRA 2 Maestro local controls include a Front Accessible Service Switch (FASS) for safe lamp replacement.

Features

- Fast, easy retrofittable wiring for any age home with any wiring
- Uses conventional 3-way and 4-way wiring to add additional remote dimmers with a matching look
- Phase selectable - works in both forward or reverse phase dimming for optimal dimming
- Proprietary RTISS Technology compensates in real time for in-coming line voltage variations
- Color change front plastics - interchangeable plastics to match the décor of any home

Sub Brand: RadioRA 2 Application: Lighting Control Type: Dimmer, multi-location/single-pole Color: Mounting: Wallbox Voltage Rating: 120 VAC Wattage: 600 W Actuator: Tapswitch Connection: Screw terminals Gang: Frequency Rating: Standard: UL, cUL, NOM, FCC, IC, COFETEL Operating Temperature: 0 to 40 degrees Celsius Special Features: Compatible with Lutron RadioRA 2 and RA2 Select lighting control systems. Controls 250 W LED, 500 W incandescent/halogen/ELV, or 400 VA magnetic low-voltage loads. Neutral Wire optional, Phase Selectable for forward or reverse phase control. Tap on to preset level; tap off. Tap twice for full on. Press, hold, and release for delayed fade-to-off. Touch rocker to adjust light level. Provides true dimming from each location with companion dimmers.