

# SAVANT



## 1" Dual 20 AMP Relay, Pigtail

GPM-H2R20120-21

SKU: 180707    UPC: 863184006608

Savant's Dual 20A Power Module (120V AC with pigtail neutral) controls and monitors up to two 20 amp circuits; ideal for outlets, kitchen appliances, lighting, and more. Supports 1-Inch On-Center Load Centers.

### Features

- Supported for use with Savant Power Systems or as part of a larger Savant Pro system.
- Compatible with Schneider Homeline, Eaton BR, Siemens, and GE Powermark Gold load centers with a one-inch on-center bus bar
- Deployment and configuration via Savant Power and Light 2.0 App or through RacePoint Blueprint
- Control Capability for loads up to 2400 VA (volt-ampere) per channel
- Built-in energy monitoring: +/- .5% revenue grade accuracy / 1 sec sample time
- Dynamic remote management of loads
- Communicates via Bluetooth Low Energy (BLE) technology
- Color LCD display for easy identification and load status
- Two switches positioned on front of module allow power to outputs A and B to be toggled manually

Location	Indoor Use Only
Input Power (powers the module)	120V AC (+/- 10%) @ 60 Hz, 0.1A max
Input Power (from feeder breaker)	120V AC @ max load power
Load Power	2400VA max per channel (20A resistive load / 1 HP max per channel)
Features of Automatic Action	Type 1.B action
Standard Configuration	Relay On/Off type loads (home automation)
Tighten Torque	3.0 Nm
Wire Type	Copper (Cu) only
Purpose of Control	Operating Control, Smart Relay Control Module or equivalent
Impulse Voltage	2500V
Temperature	32° to 104° F (0° to 40° C)
Humidity	5% to 85% Relative Humidity (non-condensing)