



IQ Hardwire 16-S

QS7131-840

SKU: 183557 UPC: 00854545006993

The IQ Hardwire 16-S allows you to encrypt and connect up to 16 hardwired zones wirelessly to the IQ Panel. Automatically learning the sensor's resistor values, it's easy to install and the perfect solution for existing systems or new construction.

Features

- Encrypted S-Line sensor technology protects signals sent to the IQ Panel while still providing support for legacy 319.5 systems
- LED lighted zones for ease of "learn-in" installation/troubleshooting
- EOL resistor learning supports 1-10K Ohm resistors.
- Up to 500 Milliamps of power for hardwired motion detectors, glass break detector, and/or sirens
- Charging circuit for back-up battery, fully supervised with power outage recover

Input Voltage	16.0VDC Plug-In Transformer Backup Battery: 12VDC 5AH Max (optional) Dimensions: 5.5" X 3.5"
Operating Temperature	32 to 122F (0 to 50C) Humidity: 95% RH Max
EOL Supervision	1K to 10K Ohm
Input Zones	16 (must have resistor)
Zone Type	N/O or N/C compatible
Auxiliary Voltage Output	12VDC @ 500mA
Tamper Zone	Optional zone input for tamper
Relay Contact	60VDC/1A Max drives siren or other device