



SAVANT

QO Single 60 AMP Relay

GPM-QP1R60240-21

SKU: 179151 UPC: 43168547048

The inCharge 60A Relay Companion Module with Current Transformer (QO™ compatible with plug-on neutral) controls a single circuit of up to 60 amps, ideal for central heating & cooling, sub-panels, EV chargers, and more.

Features

- Works with 3/4 inch Schneider/Electric Square D™ QO™ plug-on neutral load centers.
- Supported for use with InCharge Power Systems or as part of a larger Savant Pro system.
- Compatible with Savant Power Director and/or Savant Panel Bridge Controller (PBC-1000), Savant Energy Monitor (SEM)
- Deployment and configuration via Savant Power and Light 2.0 App or through RacePoint Blueprint
- Control Capability for loads up to 14400 VA (volt-ampere)
- Built-in energy monitoring: +/- .5% revenue grade accuracy / 1 sec sample time
- Dynamic remote management of loads
- Communicates via Bluetooth Low Energy (BLE) technology
- Color LCD display for easy identification and load status
- Switch positioned on front of module allows power to output to be toggled on/off manually

Temperature	32° to 104° F (0° to 40° C)
Location	Indoor Use Only
Dimensions	5" x 2.88" x 2.60"
Input Power (powers the module)	120V AC (+/- 10%) @ 60 Hz, 0.1A max
Input Power (from external source)	240V AC @ max load power
Load Power	14400VA (240VAC 60A resistive load / 3HP max)
Wireless	<ul style="list-style-type: none"> • Bluetooth 5 Low Energy (BLE) • 2.4 GHz radio frequency