



Diva Control for 0-10V LED Drivers & Fluorescent Ballasts - Snow

DVSCSTV-SW

SKU: 91977 UPC: 784276099790

This dimmer is a simple solution is designed to match existing design style switches and accessories. Easily turn the lights on and off with a paddle switch, and use the slide control to adjust the lights to the perfect level. The new Diva 0 to 10-Volt dimmer is a 0-10 VDC dimmer with 3-way functionality for 3rd party 0 to 10-Volt fixtures (LED and fluorescent), no separate power pack required. Coordinating Wallplate sold separately.

Features

- Large paddle switch with a captive linear-slide control for a standard designer-opening wallplate.
- 0 - 10 V control link controls third party fixtures.
- DVSTV- wires as single pole or 3-way, 120 - 277 V~ switch
- Patented switching technology extends product lifetime.
- High-end and low-end trim user is adjustable for optimal performance.
- Load Switching Capacity: 8A
- 0 - 10 V Sink Capacity 50 mA

Sub Brand: Diva Application: Lighting Control Type: Dimmer, 3-way/single-pole Color: Mounting: Wallbox Voltage Rating: 120 to 277 VAC Wattage: 2216 W Actuator: Paddle switch Connection: Wire Leads Gang: Frequency Rating: 60 Hz Standard: UL, CSA Operating Temperature: 0 to 40 degrees Celsius Special Features: Controls 0-10 V LED or fluorescent fixture loads, 50 mA max control current. Paddle turns on/off. Slide up to brighten, down to dim.