



resideo

Vista Residential Control Panel

VISTA-21iP

SKU: 65486 UPC: 781410887961

The high capacity, feature-rich VISTA-21iP lets you deliver more value to your customers on each and every sale. The VISTA-21iP provides up to 48 zones of protection, an on-board IP connection, graphic keypad support and dual partitions. The VISTA-21iP gives you the ability to send alarm signals and upload/download via an Internet Protocol (IP), improving the speed at which information can be delivered to and from the control panel. When used with an optional AlarmNet® LTE that snaps right on the board, the VISTA-21iP can be installed in premises without TELCO lines – guaranteeing communication independent of any infrastructure. The panel's installation advantages, innovative end-user benefits and robust system capacity make the value-priced VISTA-21iP an ideal choice for higher-end installations.

Features

- Internet alarm reporting and uploading/ downloading capability
- Supports four graphic touchscreen keypads
- Wireless keys can be programmed without using zones
- Eight on-board hardwired zones standard (15 when Zone Doubling feature is used)
 - 40 hardwired expansion zones
 - 40 wireless expansion zones
- Two independent partitions plus a common partition
 - Global arming from any system keypad
 - Go to function to view or operate one partition from the other
 - Separate partition account numbers
- 48 system user codes assignable to either partition
- 100 Event Log viewable at system keypads with time/date stamp
- Two low current on-board trigger outputs
- Supports four graphic touchscreen keypads
- Wireless keys can be programmed without using zones
- 16 output devices
 - Relays (Model 4204 Relay Modules, or 4229 Expansion Module)
- Four installer-configurable zone types allows the installer to create custom zone types by assigning all zone attributes
- Supports four-wire, and up to 16 two-wire smokes
 - Works with Sentrol CleanMe™ maintenance signal
- Multiple actions on output devices depending on system state
 - Turns lights off when system arms
 - Turns the same light on when system disarms
 - Flashes same lights when system is in alarm
- Built-in phone line cut monitor with programmable delay and annunciation options
 - Display on system keypads
 - Trigger local sounders
 - Trigger system bell
- Automatic System Load Shed
 - During extended AC power fail, the system battery will be disconnected to prevent irreversible battery failure. Reduces service calls to replace batteries.
- Dynamic Signaling

- Reduces redundant reporting to the central station when multiple reporting methods are used; i.e. digital dialer and AlarmNet radio
- Viewable on system keypads
 - Exit countdown
- Auto keypad backlighting on entry
- Keyswitch arming
- Programmable macro buttons and single-button arming
- User Scheduling
 - Auto arm/disarm
 - “User access” time windows
- Chime by zone
- VIP Module allows system control from any touchtone phone
- Fully compatible with Resideo Total Connect Remote Services

Application	Residential security systems
Number of Zones after Expansion	40 hardwire expansion zones, 40 wireless expansion zones
Product Height	14.5"
Product Width	3"
Battery Voltage	12 DC