



resideo

VISTA 20P Control Panel Kit

V20PACK

SKU: 62089 UPC: 781410203167

The high capacity, feature-rich VISTA-20P lets you deliver more value to your customers on each and every sale with up to 48 zones of protection, Internet uploading/downloading, graphic keypad support and dual partitions. VISTA-20P gives you the ability to send alarm signals and upload/download via an Internet Protocol (IP), improving the speed at which information can be delivered to and from the control panel. In addition, the VISTA-20P, used with an AlarmNet Internet or 4G communicator can be installed in premises without TELCO lines. The panels installation advantages, innovative end-user benefits and robust system capacity make the value-priced VISTA-20P an ideal choice for higher end installations.

Features

- Vista 20P Control Panel
- 6150 Keypad
- IS-335 Motion Detector
- Wave2 Siren
- Battery
- Jack and Cord

General:	<p>IP alarm reporting and uploading/ downloading capability for Internet and Intranet use via iGSMV4G, 7845i-ENT, GSMV4G or GSMX4G</p> <p>Supports four graphic touchscreen keypads</p> <p>Wireless keys can be programmed without using zones</p> <p>Eight on-board hardwired zones standard (15 when Zone Doubling feature is used)</p> <ul style="list-style-type: none"> - 40 hardwire expansion zones - 40 wireless expansion zones <p>Two low current on-board trigger outputs</p> <p>100 Event Log viewable at system keypads with time/date stamp</p> <p>48 system user codes assignable to either partition</p> <p>Expandable to 48 total zones when used with hardwired and/or wireless expansion modules</p> <p>Two independent partitions plus a common partition</p> <ul style="list-style-type: none"> - Global Arming from any system keypad - Go to function to view or operate one partition from the other - Separate partition account numbers <p>16 output devices</p> <ul style="list-style-type: none"> - Relays (Model 4204 Relay Modules, or 4229 Expansion Module) <p>Four installer-configurable zone types allows the installer to create custom zone types by assigning all zone attributes</p> <p>Supports four-wire and up to 16 two-wire smokes</p> <ul style="list-style-type: none"> - Works with Sentrol CleanMe maintenance signal <p>Multiple actions on output devices depending on system state</p> <ul style="list-style-type: none"> - Turns lights off when system arms - Turns the same light on when system disarms - Flashes same lights when system is in alarm <p>Built-in phone line cut monitor with programmable delay and annunciation options</p> <ul style="list-style-type: none"> - Display on system keypads - Trigger local sounders - Trigger system bell
Security Dealer Features:	<p>Automatic System Load Shed</p> <ul style="list-style-type: none"> - During extended AC power fail, the system battery will be disconnected to prevent irreversible battery failure. Reduces service calls to replace batteries. <p>Dynamic Signaling</p> <ul style="list-style-type: none"> - Reduces redundant reporting to the central station when multiple reporting methods are used; i.e. digital dialer and AlarmNet radio
Valuable End-User Features:	<p>Viewable on system keypads:</p> <ul style="list-style-type: none"> - Exit countdown - Time and date display* - Event log* <p>Auto keypad backlighting on entry</p> <p>Keyswitch arming</p> <p>Programmable macro buttons and single-button arming</p> <p>Supports a variety of wireless remote controls for single-button operation</p> <p>User Scheduling</p> <ul style="list-style-type: none"> - Latchkey reports to pagers - Auto arm/disarm - ?User access"" time windows <p>VIP Module allows system control from any touchtone phone</p> <p>Chime by zone</p>