

# DENON



## 2-Channel Integrated Amplifier w/ DAC and USB

PMA1700NE

SKU: 179448    UPC: 747192137632

Featuring advanced ultra-high current single push-pull circuit power, Advanced AL32 Processing, and MM/MC phono equalizer, the Denon PMA-1700NE integrated amplifier delivers extraordinary sound quality with precise detail. Engineered with premium Denon technologies, this amplifier drives two channels at 140W. Advanced AL32 Processing Plus delivers the richly detailed sound the artist intended. This integrated amplifier offers compatibility with the widest range of 6 speaker types and impedances for operational stability.

To accurately synchronize digital circuits, the PMA- 1700NE provides USB-DAC functions that support high resolution up to 11.2-MHz DSD and 384- kHz/32-bit PCM input signals. Crafted with exceptional quality, the DAC suppresses jitter and ensures optimal precision in D/A conversion.

### Features

- High-power 140W integrated amplifier
- Advanced AL32 Processing Plus
- USB-DAC
- High-precision electrical controls
- MM and MC phono equalizer
- Optical and coaxial digital inputs
- External pre-amp input terminals
- TV auto standby (digital input)
- Six-block chassis configuration and direct mechanical ground construction
- Digital isolator
- Analog mode

Dimensions	17.1 x 16.1 x 5.3in
Rated Output Power	70W + 70W (8ohm,20Hz-20kHz,THD0.07%) 140W + 140W (4ohm, 1kHz, THD0.7%)
Speaker Impedance	A or B : 4 ~ 16ohm A + B : 8 ~ 16ohm
Frequency Response	5Hz - 100kHz (0~ -3dB)
Power Consumption	295W
Power Amplifier Circuit	New UHC-MOS Single Push Pull (7)
Pre Amplifier Circuit	Variable Gain Preamplifier (OP AMP)
Bass / Treble / Mid / Balance Control	Yes / Yes / No / Yes
DAC Circuit	PCM1795
Digital Filter	Fixed
Digital Processing	Advanced AL32 Processing Plus
Optical input / output	2 / 0 (192kHz/24bit)
Coaxial input / output	1 / 0 (192kHz/24bit)