

SONANCE



DSP 2-150 MKII Multi-Channel Power Amplifier

93378

SKU: 179239 UPC: 041093933783

The new line of DSP amplifiers feature SonARC (Sonance Advanced Room Correction), which offers hundreds of EQ presets designed specifically for Sonance speakers available through simple pull down menus. The presets enable effortless DSP without the need for additional hardware, software, and more importantly time. Additionally, should there be a need for further customization, SonARC provides a 10-band parametric EQ to optimize sonic performance in any space.

Features

- Multi-Channel - 2 x Stereo pair
- Compact form factor allows for space savings in the equipment rack with ample power to the speakers.
- Full array of input/output connectivity for maximum installation flexibility: Line input/loop outputs; IP, IR, audio and voltage triggers; Ethernet jack for network connectivity
- Bridgeable channels for applications when even more power is required.
- RMS @ 8 Ohms 150 watts (2 channels driven)
- RMS @ 4 Ohms 224 watts (2 channels driven)
- RMS @ 8 Ohms Bridged 473 watts
- High resolution 24 bit/96 kHz processing DAC capable of 4608 KBPS audio playback.
- Rack ears and removable feet included.
- Dimensions + Feet (WxHxD) 8.625" x 2.125" x 16.8125" (219mm x 54mm x 427mm)