



3-Input 40-Watt Mixer Amplifier

MA40G

SKU: 25490 UPC: 612079187096

Small and compact, and engineered for reliability, the AtlasIED MA40G amplifier is the perfect choice for distributed business paging and background music (BGM) systems, and small to medium speech privacy systems. It provides 40W into a 70.7V/100V line and has three total inputs including a balanced mic/line input featuring phantom power and variable mute sensitivity control as well as two unbalanced, summing line level inputs. Additional features include Removable Level Controls with set it and forget it security cover, contact closure mute terminals, and a global (100VAC-240VAC) power supply. The MA series of amplifiers are part of a new line from AtlasIED that are designed from the ground up and include the important features professional installation personnel require to meet or exceed their customers expectations.

Features:

- One Balanced Mic/Line/Tel Input w/Phantom Power
- 2 Unbalanced, Summing Line Level Inputs
- Variable VOX Mute Sensitivity Control for Input 1
- Contact Closure Mute Terminals
- Global Power Supply, 100VAC-240VAC ~ 50/60Hz
- Compact 1RU, 1/2 Rack

Frequency Response	50Hz - 20kHz
Inputs	Three
Connector Type	Phoenix and RCA
Output Power	40 Watts
Voltage Compatibility	Universal