



Complete Control Handheld Touch Screen w/ Hard Buttons & Voice Control

MX-4000

SKU: 184272 UPC: 656787705272

This premium handheld controller presents a streamlined design with both a touch screen and hard buttons for optimal hand feel and functionality. The hard buttons deliver the convenience of control without having to look at the screen. When separated from the charging base, the touch screen features back-side finger grips to complete a perfect fit. The vibrant 5-inch color LCD screen delivers high-resolution graphics and ease of use. With enhanced processing speed, the MX-4000 enables quick response to simple one-touch or voice commands, and the built-in mic and speaker communicate seamlessly with Amazon Alexa and Comcast Xfinity. Pickup sensor wakes the device and ensures a premium user experience. The MX-4000 is able to control an entire residential or commercial URC system.

Features

- Vibrant 5" touch screen LCD
- Fast setup of complex systems via Complete Control® PC Editor
- Built-in mic and speaker communicate seamlessly using voice command via Amazon Alexa and Comcast Xfinity
- Customizable user interface for any activity
- Narrow band RF compatible with URC 418MHz RF Base Stations

Processor/Memory	Flash Memory 8GB
Wi-Fi	Quick Connect 2.4 GHz [For Voice Control]
LCD	5.0" TFT-LCD (720 x 1280), 16.7M colors
IR Range	Up to 50 feet, depending on the environment
RF Range	Up to 100 feet, depending on the environment
RF Frequency	418 MHz
Microphone	2 CH MIC
Speaker	Mono, 1.5 watt
Battery	Lithium-polymer, 3.7V, 4500mAh
Battery Charging Time	4 Hours
Power	2.0A / 5.0V
Operating Temp	0~50°C (non-condensing)
Dimensions	8.27" (210.06mm) W x 4.41" (112.01mm) H x 1.28" (32.51mm) D
Weight	11.5oz (with battery loaded)