



JASCO

Pro Series In-Wall Add-on Switch

59378

SKU: 181476 UPC: 030878593786

Create a multi-way lighting control setup within your home or business to control your smart lighting with the JascoPro Series In-Wall Add-on Switch. This add-on rocker switch shares control of the same wired load as a connected primary JascoPro Series in-wall switch or dimmer to create a multi-way lighting control configuration. If the connected JascoPro Series primary switch is a part of a smart home automation network, the In-Wall Add-on Switch remains capable of controlling the wired load. The In-Wall Add-On Switch cannot function as a standalone switch and must be included into or create a multi-way wiring configuration. The Switch can be included into multi-way wiring configurations up to 6-way control, with up to 4 In-Wall Add-on Switches being paired with a single JascoPro Series switch. If multiple In-Wall Add-on Switches are a part of a single multi-way configuration, the Add-On Switches must be installed no more than 75ft away from each other, no more than 200ft away from the primary switch, and the entire configuration must not exceed 300ft from one end to the other.

Features

- Add-on rocker switch provides additional local On/Off control of a wired load when paired with a primary JascoPro Series switch
- Supports 2, 3, 4, 5, or 6-way wiring configurations
- Compatible with JascoPro Series Z-Wave Plus, Zigbee, and Wi-Fi in-wall devices when paired with a similarly compatible primary switch
- Each Add-On Switch must be installed within 200ft of the primary switch
- For 3, 4, 5, or 6-way configurations, an Add-On switch must be within 75ft of each directly wired Add-On switch
- Total multi-way wiring interconnection must fit not exceed 300ft
- Uses a standard rocker wallplate, sold separately
- Interchangeable rocker switch – white and light almond paddles included