



RadioRA 2 8A Neutral Switch - Ivory

RRD-8ANS-IV

SKU: 36687 UPC: 27557771689

RadioRA 2 Maestro local controls function much like standard dimmers and switches, but can be controlled as part of a lighting control system. Local lighting controls are useful in locations where single circuits of lighting need to be dimmed or switched. Local fan speed controls are useful in locations where control of a single ceiling paddle fan is needed.

RadioRA 2 Maestro dimmers incorporate advanced features such as fade-on/fade-off, delayed long fade-to-off, and rapid full-on. RadioRA 2 Maestro local controls include a Front Accessible Service Switch (FASS) for safe lamp replacement. RadioRA 2 Maestro local controls install in single pole or multi-location applications.

Features

- 8 A Neutral Wire Electronic Switch
- Dimmers and switches communicate with the system through Radio Frequency (RF) and must be located within 30 ft (9 m) of a repeater.
- System devices operate on frequencies between 431.0 MHz and 437.0 MHz.
- Use Lutron Designer (Claro or Satin Colors) wallplates or designer-style wallplates from other manufacturers.

*Wall plate sold separately

General Information:	
Product Type	Wireless Switch
Miscellaneous:	
Application/Usage	Light Controlling Motor Controlling
Certifications & Standards	UL CSA cUL NOM FCC IC COFETEL
Physical Characteristics:	
Form Factor	Wall Mount
Power Description:	
Current Rating	8 A
Input Voltage	120 V AC
Warranty	
Standard Warranty	1 Year